

## Specification

Electrical	Voltage	100V ~240V
	Power consumption	500W
	Halogen lamp	18R, 380W
Light Source	Lamp life span	1500H
	CCT	8000K
	DMX512	26ch/23ch(switchable)
Control Mode	Master/slave	√
	Auto	√
	RDM / ARTNET	√
	Fixed Gobo Wheel 1	9 gobos+ white open + Shake + bi-direction flow effect;
	Fixed Gobo Wheel 2	10 gobos+ 4 different size beam holes + Shake + bi-direction flow effect;
	Rotation Gobo Wheel	6 gobos + water wave glass endless rotation+ white open + bi-direction flow effect.
Optical System	Color wheel	12 color+ 2 CTO + 1 CTB + 1 CMY+ White open + semi-color effect;
	Prism	8 facet + 16 facet
	Shutter	1~20t/s
	Dimmer	0-100%
	Focus/Zoom	√
	Beam angle	2.3° - 50 °
	X/Y scan	Three-phase motor, pan 540°, tilt:270°, photoelectric reset and correction

			1pc screen touch display + 4pc buttons, LCD color screen, can set the channel mode, horizontal vertical inversion, back screen, signal hint, switch in both Chinese and English, automatic screen off/lasting bright screen, display channel number, record light source time, boot time and fault inspection, scene setting, the software version information, restore factory Settings
	Display		
	Signal interface		3 pin
	Power interface		1 in;1 out powercon
Safety protection	the power will be cut off automatically with system error		when the fixture is overheating or
Machine W. Size	23.45kg	409.9*323.9*670.5mm	
Environment& safty	Level of Protection		IP20
	Stock		Clean and dry place
	Running temp.		-10°C~40°C
26 channel mode		23channel mode	
1	Pan	1	Color
2	Pan fine-tuning	2	Dimmer
3	Tilt	3	Strobe
4	Tilt fine-tuning	4	C
5	Pan and tilt speed	5	M
6	Frost	6	Y
7	Dimmer	7	Gobo
8	Strobo	8	Effect Gobo
9	C	9	Rotation gobo
10	M	10	Gobo self rotate
11	Y	11	Prism 1

12	Color 1	12	Prism 1 rotation
13	Color 2	13	Prism 2
14	Color 3	14	Prism 2 rotation
15	Color 4	15	amplification
16	Gobo	16	focusing
17	Effect Gobo	17	Frost
18	Rotation Gobo	18	Pan
19	Gobo self -rotate	19	Pan fine-tuning
20	Prism 1	20	Tilt
21	Prism 1 self -rotate	21	Tilt fine-tuning
22	Prism2	22	Pan and tilt speed
23	Prism 2 self -rotate	23	reset
24	amplification		
25	focusing		
26	Reset		

## FAQ

### **1.Can you do ODM, OEM?**

yes, sure.

### **2.Is it OK to print my logo on stage light product?**

Yes. Please inform us formally before our production and confirm the design firstly based on our sample.

### **3.Are you a factory or trading company?**

We are a factory.